
### LUMINAIRE

SEQUOIA LIGHTING SYSTEMS

PENDANT

# DESIGN



### SPECIFICATIONS

Luminaire Name: Alexandria Pendant Description: Pendant style luminaire. Housing is heavy duty cast

<sup>31</sup> aluminum with internal specular Alzack reflector. Luminaire is provided with a heavy duty cast aluminum leveling plumizer. The prismatic globe provides Type III or V light distribution.

# Material:AluminumAA319.OFRefractor:Acrylic / Polycarbonate UV stabilized / GlassWattage/Lamping:

- Mercury Vapor (100, 175 or 250 watt)
- High Pressure Sodium (70, 100, 150, 200 or 250 watt)
- Metal Halide (100, 175, 250 watt)
- QL Induction (55, 85 watt)

SEOUOIA LIGHTING

• Incandescent

Distribution:SymmetricorAsymmetricVoltage:120,208,240,277or480voltOptions:DecorativeHood/Housesideshield/Photocontrol

/Fusing

CORPORATION


Dimensions:AlldimensionsarenominalPhotometry:AvailableuponrequestonI.E.S.formatteddiskWarranty:Fixture shall be warranted to be free of defects for two

years. Ballast components shall carry the ballast manufacturer's limited warranty









#### DECORATIVE SHIELD OPTIONS

#### FINISH

#### Three Stage:

- Cleaned and Etched
- Primered
- Powder coated or wet painted

Colors: Black, bronze, green, gray, swedish iron

\* Custom colors available

#### APPLICATIONS

- Roadways
- Parking Lots
- Perimeter Ltg..
- Transportation Terminals
- Office Complexes
- · School Campus
- · Shopping Malls
- Hotels/Motels
- · Industrial Sites
- · Commercial Developments
- · Waterfront Areas
- Parks/Recreational Areas
- · Architectural Landscape Ltg..

MANUFACTURERS OF QUALITY LIGHTING PRODUCTS

13644 George Blvd, Suite 1, Victorville, CA, 92394 (760) 246-5213 FAX (760) 246-5294 www.sequoialighting.com

## LUMINAIRE

SEQUOIA LIGHTING SYSTEMS

PENDANT

ORDERING NUMBER LOGIC

#### -6 -0 -0 -0 -1 -5 -PC -V -C -O -5 -PO -2 -0 -M1 Example: LP400 $(\widehat{E})$ $(\widehat{G})$ $(\widehat{H})$ (B) (Ĉ) (D) $(\overline{F})$ $(\mathbf{I})$ $(\mathcal{J})$ (K) (Ľ) $(\widehat{\mathbf{M}})$ (N) $(\overline{0})$ (A)(A) DESIGN I.D. \_Top Right Corner of Cutsheet 7 = 150 Watts (K) LIGHTNING ARREST OR OPTION 8 165 Watts = 0 = None BALLAST TYPE $(\mathbf{B})$ 9 = 175 Watts A = (1) 120V Arrestors High Pressure Sodium 10 = 200 Watts В (1) 240V Arrestors = 20 = 120V High Power Factor (150W and below) (2) 120V Arrestors 11 = 250 Watts C = 21 = 120V Regulated High Power Factor = 310 Watts 12 D = (2) 240V Arrestors = 120V Normal Power Factor 22 13 = 400 Watts (Î) <u>LAMP</u>OPTION 23 = 240V High Power Factor 00 1000 Watts 24 = 240V Regulated Power Factor 15 = 1500 Watts 0 = No Lamp Included 240V Lag Norma Power Factor 25 = C Clear Lamp Included 26 = 208V Regulated Power Factor (D) PHOT OCONTROL Rapid Start Lamp Included R 27 = 277V Regulated Power Factor 0 Without Photo Control F = Coated Lamp Included = 480V Regulated Power Factor 28 1 = With Photo Control Μ Master Color Lamp Included M1 = Multi-volt Regulated High Power Factor Ρ Protected Metal Halide (E) INTERNAL GLASS REFRACT Wired 120V OR Lamp Included H6 = 6.6 AMP 0 = None W White Son HPS Lamp Included 1 =Yes Q = QL Induction Lamp Included Metal Halide = 120V CWA High Power Factor 30 (F) GLOBE/LENS TYPE PRISMA TIC (M) FUSE OPTION 31 = 240V CWA High Power Factor **0** = Non Prismatic No Fusing 0 208V High Power Factor 32 = **1** = Prismatic 1 = (1) 5 Amp Fuse 33 = 277V CWA High Power Factor 2 = (2) 5 Amp Fuse 34 Multi-volt CWA High Power Factor (G) INTERNAL GLOBE REFLECT OR 3 = (1) 10 Amp Fuse Wired For 120V = None 0 4 = (2) 10 Amp Fuse M6 = 6.6 AMP 1 =Yes 5 = (1) 15 Amp Fuse 6 = (2) 15 Amp Fuse Mercury Vapor (ÎI) IES LIGHT DISTRIBUTION = 7 (1) 20 Amp Fuse 120/240 Regulated High Power Factor 02 = 2 Type II 8 = (2) 20 Amp Fuse = Wire For 120V 3 = Type III 03 240/480 Regulated High Power Factor (N) SHADE TYPE 5 = Type V Wire For 240V 0 = None 04 = 208V Regulated High Power Factor (Î) GLOBE/LENS 1 = #P1 05 = 277V Regulated High Power Factor Glass Clear GC = 2 = #P2 06 120V Lag Auto Normal Power Factor GW =Glass White 3 = #P3 07 = Multi-volt Regulated High Power Factor PC = Polycarbonate Clear (Translucent) 4 = #P4 Wired For 120V PW =Polycarbonate White 5 = #P0 (As Shown on Fixture) V6 = 6.6 AMP AC = Acrylic Clear 6 = Custom( Per Specification) Acrylic White AW = QL Induction (Please Specify Kelvin) SM = Smoked ALUMINUM GLOBE ADAPT OR $(\bigcirc)$ **Q1** = 120V 0 None = Q2 = 240V $(\overline{J})$ paint 8" To 6" 1 = Q6 = 6.6 AMP BL Black 9 3/8" To 8" 2 BR = Bronze 3 8" To 7" Incandescent VR = Verde = Insert (Plastic) 4399&4599 4 IN = Specify Wattage GR = Green GY = $(\overline{P})$ HOUSE SIDE SHIELD Gray WH = White 0 = None LAMP WATT AGE $(\mathbb{C})$ RD = Red 1 =Yes 35 Watts = BU = Blue 50 Watts

3 = 55 Watts 70 Watts 4

2

- 5
- 85 Watts
- 6 = 100 Watts

CORPORATION

SEQUOIA LIGHTING

MANUFACTURERS OF QUALITY LIGHTING PRODUCTS

Custom (Per Specification)

13644 George Blvd, Suite 1, Victorville, CA, 92394 (760) 246-5213 FAX (760) 246-5294 www.sequoialighting.com

CC =

Revisior